



K097 MAC/3UU
K098 MAC/V45U
K099 WHP/3UU
K100 WHP/V45U

Mini centraline larga banda schermate ed alimentatore incorporato, con 1-3-4 ingressi regolabili ad amplificazioni VHF-UHF separate. Possibilità di passaggio di +cc su tutti gli ingressi tramite inseritore esterno ICC. Sono centralini adatti per piccoli impianti centralizzati. I modelli MAC/RSV45 e MAC/RS345 sono indicati come amplificatori per antenne logaritmiche. Il mod. MAC/PLV45 è indicato come amplificatore di linea per rinforzare discese lunghe in impianti centralizzati.

Shielded wide band mini headends with built-in power supply and 1-3-4 adjustable inputs with independent VHF and UHF amplification. There is provision for switching to +d.c. on all inputs through external inserter ICC. These headends are suitable for small collective systems. Models MAC/RSV45 and MAC/RS345 are suitable as amplifiers for logarithmic antennas. Model MAC/PLV45 can be used as line amplifier to boost long down cables in collective systems.

Cod. Modello Code Model	Ingressi Regolabili Adjustable Inputs	Guadagno Gain	Figura di Rumore Noise Figure	Livello d'Uscita Output Level	Corrente Max Tele Alimentata Current Max Tele Powered	Confezione Confection
K097 MAC/3UU	III ^a UHF UHF	22 dB 24 dB 24 dB	2 dB 6 dB 6 dB	108 dBμV 110 dBμV 110 dBμV	45 mA	25
K098 MAC/V45U	VHF IV ^a V ^a UHF	22 dB 24 dB 24 dB 24 dB	2,5 dB 6 dB 6 dB 6 dB	108 dBμV 110 dBμV 110 dBμV 110 dBμV	45 mA	25
K099 WHP/3UU	III ^a UHF UHF	38 dB 40 dB 40 dB	3,5 dB 7,5 dB 7,5 dB	116 dBμV 119 dBμV 119 dBμV	140 mA	25
K100 WHP/V45U	I ^a III ^a IV ^a V ^a UHF	38 dB 38 dB 40 dB 40 dB 40 dB	3,5 dB 3,5 dB 7,5 dB 7,5 dB 7,5 dB	116 dBμV 116 dBμV 119 dBμV 119 dBμV 119 dBμV	140 mA	25